# Product data sheet Characteristics

### **ABL8RPS24100**

Regulated Switch Power Supply, 1 or 2-phase, 100..500V, 24V, 10 A





#### Main

Widiri		
Range of product	Modicon Power Supply	
Product or component type	Power supply	
Power supply type	Regulated switch mode	
Nominal input voltage	100120 V AC single phase, terminal(s): N-L1 200500 V AC phase to phase, terminal(s): L1-L2	
Input voltage limits	170550 V AC 85132 V AC	
Rated power in W	240 W	
Output voltage	24 V DC	
Power supply output current	10 A	
Permissible temporary current boost	1.5 x ln (for 4 s)	
Anti-harmonic filter	Low frequency harmonic currents	

#### Complementary

Inrush current	30 A		
Power factor	0.68 at 240 V AC 0.69 at 120 V AC		
Efficiency	87 %		
Output voltage adjustment	2428.8 V adjustable		
Power dissipation in W	31 W		
Provided equipment	Power factor correction filter conforming to IEC 61000-3-2		
Output protection type	Against overload, protection technology: manual or automatic reset Against overvoltage, protection technology: 3032 V, manual reset Against short-circuits, protection technology: manual or automatic reset Against undervoltage, protection technology: tripping if U < 21.6 V Thermal, protection technology: automatic reset		
Connections - terminals	Removable screw terminal block: $2 \times 2.5 \text{ mm}^2$ , for diagnostic relay Screw type terminals: $3 \times 0.53 \times 4 \text{ mm}^2$ , (AWG 22AWG 12) for input connection Screw type terminals: $1 \times 0.51 \times 4 \text{ mm}^2$ , (AWG 22AWG 12) for input ground connection		

Screw type terminals: 4 x 0.54 x 4 mm², (AWG 22AWG 12) for output connect Screw type terminals: 1 x 0.51 x 4 mm², (AWG 22AWG 12) for output ground			
Status LED	1 LED (green and red)output voltage 1 LED (green, red and orange)output current		
Depth	145 mm		
Height	125 mm		
Width	86 mm		
Net weight	1 kg		
Output coupling	Parallel Series		
Marking	CE		
Mounting support	35 x 7.5 mm symmetrical DIN rail 35 x 15 mm symmetrical DIN rail		

Vertical

#### Environment

Operating position

Standards	UL 508 CSA C22.2 No 60950-1
Product certifications	CCSAus
	EAC
	KC
	RCM
	UL
Environmental characteristic	EMC conforming to EN 61000-6-1
	EMC conforming to EN 61000-6-3
	EMC conforming to EN 55024
	EMC conforming to EN/IEC 61000-6-4
	EMC conforming to EN/IEC 61204-3
	Safety conforming to EN/IEC 60950-1
	Safety conforming to EN/IEC 61204-3
	Safety conforming to SELV
Operating altitude	2000 m
IP degree of protection	IP20 conforming to EN/IEC 60529
Ambient air temperature for operation	5060 °C (with derating factor)
·	-2550 °C (without)
Ambient air temperature for storage	-4070 °C
Relative humidity	090 % during operation
	095 % in storage
Dielectric strength	3500 V between input and ground
	4000 V between input and output
	500 V between output and ground

### Packing Units

Package 1 Weight	1.657 kg	
Package 1 Height	1.100 dm	
Package 1 width	1.670 dm	
Package 1 Length	1.820 dm	

#### Offer Sustainability

Sustainable offer status	Green Premium product	
REACh Regulation	REACh Declaration	
REACh free of SVHC	Yes	
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope) EU RoHS Declaration	
Mercury free	Yes	
RoHS exemption information	Yes	
China RoHS Regulation	China RoHS declaration	
Environmental Disclosure	Product Environmental Profile	

End of Life Information	

#### Contractual warranty


Warranty	18 months
•	

## Product data sheet ABL8RPS24100

### Dimensions Drawings

### Regulated Switch Mode Power Supplies

#### Dimensions




ABL 8	a in mm	a in in.	b in mm	b in in.
RPS24030	125	4.92	45	1.77
RPS24050	125	4.92	56	2.20
RPS24100	145	5.71	86	3.39
RPM24200	145	5.71	146	5.75
WPS24200	160	6.30	96	3.78
WPS24400	160	6.30	166	6.54

### Product data sheet Connections and Schema

### **ABL8RPS24100**

### Regulated Switch Mode Power Supply

### Internal Wiring Diagram




### Product data sheet Connections and Schema

### **ABL8RPS24100**


### Regulated Switch Mode Power Supply

#### Line Supply Wiring Diagram


Single-phase (L-N) 100 to 120  $\rm V$ 



Phase-to-phase (L1-L2) 200 to 500 V



Single-phase (L-N) 200 to 500 V




### **ABL8RPS24100**

#### Regulated Switch Mode Power Supplies


#### Series or Parallel Connection

#### Series Connection



(1) Two Shottky diodes Imin = power supply In and Vmin = 50 V

#### Parallel Connection



Family	Series	Parallel
ABL 8RPS/8RPM/8WPS	2 products max. (1)	2 products max.

NOTE: Series or parallel connection is only recommended for products with identical references.

 $For better\ availability,\ the\ power\ supplies\ can\ also\ be\ connected\ in\ parallel\ using\ the\ ABL8RED24400\ Redundancy\ module.$ 

## Product data sheet Performance Curves

### **ABL8RPS24100**


#### Regulated Switch Mode Power Supplies

#### Derating

The ambient temperature is a determining factor that limits the power an electronic power supply can deliver continuously. If the temperature around the electronic components is too high, their life will be significantly reduced.

The nominal ambient temperature for the Universal range of Phaseo power supplies is 50°C. Above this temperature, derating is necessary up to a maximum temperature of 60°C.

The graph below shows the power (in relation to the nominal power) that the power supply can deliver continuously, depending on the ambient temperature.



X Maximum operating temperature (°C)

ABL 8RPM, ABL 8RPS, ABL 8WPS mounted vertically

Derating should be considered in extreme operating conditions:


- Intensive operation (output current permanently close to the nominal current, combined with a high ambient temperature)
- Output voltage set above 24 Vdc (to compensate for line voltage drops, for example)
- Parallel connection to increase the total power

### **ABL8RPS24100**

#### Regulated Switch Mode Power Supply


#### **Load Limit**

Manual Reset Protection Mode





(1) Boost 4s





(1) Boost 4s





This type of operation is described in detail in the user manual, which can be downloaded from the website.