

# RBC6

APC Replacement Battery Cartridge, VRLA battery, 11Ah, 12VDC, 2-year warranty



## Overview

Lead time	Usually in Stock
-----------	------------------

## Main

Product or Component Type	Replacement battery cartridge
Number of cables	1
Battery Type	Lead-Acid battery
Provided Equipment	All required connectors Battery recycling guide Reusable packaging Installation guide

## Physical

Color	Black
Height	3.70 in (9.4 cm)
Width	5.98 in (15.2 cm)
Depth	7.72 in (19.6 cm)
Net Weight	16.93 lb(US) (7.68 kg)
Mounting Mode	Not rack-mountable
USB compatible	No

## Environmental

Ambient Air Temperature for Operation	32...104 °F (0...40 °C)
Operating altitude	0...10000 ft
Relative Humidity	0...95 %
Ambient Air Temperature for Storage	5...113 °F (-15...45 °C)
Storage altitude	0...50000 ft (0.00...15240.00 m)
Storage Relative Humidity	0...95 %

## Batteries & Runtime

Battery Slots Empty	0
Included Battery Modules	0
RBC Quantity	1

## Ordering and shipping details

Category	11309-APC RESALE PRODUCTS
Discount Schedule	APC1
GTIN	731304003281
Returnability	No

## Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	6.89 in (17.5 cm)
Package 1 Width	10.20 in (25.9 cm)
Package 1 Length	11.89 in (30.2 cm)
Package 1 Weight	18.63 lb(US) (8.45 kg)

## Offer Sustainability

Sustainable offer status	Green Premium product
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to <a href="http://www.P65Warnings.ca.gov">www.P65Warnings.ca.gov</a>
REACH Regulation	<a href="#">REACH Declaration</a>
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope) <a href="#">EU RoHS Declaration</a>
Environmental Disclosure	<a href="#">Product Environmental Profile</a>
Circularity Profile	<a href="#">End Of Life Information</a>
Take-back	Take-back program available

## Contractual warranty

Warranty	2 years repair or replace
----------	---------------------------