## **SIEMENS**

## **Data sheet**

## 6ES7331-7NF10-0AB0



SIMATIC S7-300, Analog input SM 331, isolated, 8 AI;  $\pm$ -5/10V, 1-5 V,  $\pm$ 20 mA, 0/4 to 20 mA, 16 bit, Single rooting (60 V COM.), 4-channel operation: 10 ms, 8-channel operation: 23-95ms, 1x 40-pole

Figure similar

Supply voltage	
Load voltage L+	
Rated value (DC)	24 V
<ul> <li>Reverse polarity protection</li> </ul>	Yes
Input current	
from load voltage L+ (without load), max.	200 mA
from backplane bus 5 V DC, max.	100 mA
Power loss	
Power loss, typ.	3 W
Analog inputs	
Number of analog inputs	8
permissible input voltage for voltage input (destruction limit), max.	75 V; 35 V continuous, 75 V for max. 1 s (mark to space ratio 1:20)
permissible input current for current input (destruction limit), max.	40 mA
Input ranges	
<ul> <li>Voltage</li> </ul>	Yes
<ul> <li>Current</li> </ul>	Yes
<ul> <li>Thermocouple</li> </ul>	No
<ul> <li>Resistance thermometer</li> </ul>	No
Resistance	No
Input ranges (rated values), voltages	
• 0 to +10 V	No
• 1 V to 5 V	Yes
<ul><li>— Input resistance (1 V to 5 V)</li></ul>	10 ΜΩ
• 1 V to 10 V	No
• -1 V to +1 V	No
• -10 V to +10 V	Yes
<ul><li>— Input resistance (-10 V to +10 V)</li></ul>	10 ΜΩ
• -2.5 V to +2.5 V	No
• -250 mV to +250 mV	No
• -5 V to +5 V	Yes
— Input resistance (-5 V to +5 V)	10 ΜΩ
• -50 mV to +50 mV	No
● -500 mV to +500 mV	No
• -80 mV to +80 mV	No
Input ranges (rated values), currents	
• 0 to 20 mA	Yes
<ul><li>— Input resistance (0 to 20 mA)</li></ul>	250 Ω
• -10 mA to +10 mA	No

• -20 mA to +20 mA	Yes
<ul><li>— Input resistance (-20 mA to +20 mA)</li></ul>	250 Ω
• -3.2 mA to +3.2 mA	No
• 4 mA to 20 mA	Yes
— Input resistance (4 mA to 20 mA)	250 Ω
Input ranges (rated values), thermocouples	
• Type B	No
• Type C	No
• Type E	No
• Type J	No
• Type K	No
• Type L	No
• Type N	No
• Type R	No
Type S	No
• Type T	No
• Type U	No
<ul> <li>Type TXK/TXK(L) to GOST</li> </ul>	No
Input ranges (rated values), resistance thermometer	
• Cu 10	No
• Ni 100	No
• Ni 1000	No
• LG-Ni 1000	No
• Ni 120	No
• Ni 200	No
• Ni 500	No
• Pt 100	No
• Pt 1000	No
• Pt 200	No
• Pt 500	No
Input ranges (rated values), resistors	
• 0 to 150 ohms	No
• 0 to 300 ohms	No
• 0 to 600 ohms	No
• 0 to 6000 ohms	No
Cable length	
Cable length	
shielded, max.	200 m
shielded, max.	200 m
shielded, max.  Analog value generation for the inputs	200 m
shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel	
shielded, max.  Analog value generation for the inputs	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/15 bit
shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel	
<ul> <li>shielded, max.</li> <li>Analog value generation for the inputs</li> <li>Integration and conversion time/resolution per channel</li> <li>Resolution with overrange (bit including sign), max.</li> </ul>	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/
<ul> <li>shielded, max.</li> <li>Analog value generation for the inputs</li> <li>Integration and conversion time/resolution per channel</li> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> </ul>	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/
<ul> <li>shielded, max.</li> <li>Analog value generation for the inputs</li> <li>Integration and conversion time/resolution per channel</li> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Basic conversion time (ms)</li> </ul>	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign Yes; 23 / 72 / 83 / 95 ms 10 ms (4-channel mode); 95/83/72/23 ms (8-channel mode)
shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel     Resolution with overrange (bit including sign), max.      Integration time, parameterizable     Basic conversion time (ms)     Interference voltage suppression for interference	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign Yes; 23 / 72 / 83 / 95 ms 10 ms (4-channel mode); 95/83/72/23 ms (8-channel mode)
shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel     Resolution with overrange (bit including sign), max.      Integration time, parameterizable     Basic conversion time (ms)     Interference voltage suppression for interference frequency f1 in Hz  Encoder	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign Yes; 23 / 72 / 83 / 95 ms 10 ms (4-channel mode); 95/83/72/23 ms (8-channel mode)
shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel     Resolution with overrange (bit including sign), max.      Integration time, parameterizable     Basic conversion time (ms)     Interference voltage suppression for interference frequency f1 in Hz  Encoder  Connection of signal encoders	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign Yes; 23 / 72 / 83 / 95 ms 10 ms (4-channel mode); 95/83/72/23 ms (8-channel mode)
shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel     Resolution with overrange (bit including sign), max.      Integration time, parameterizable     Basic conversion time (ms)     Interference voltage suppression for interference frequency f1 in Hz  Encoder	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign Yes; 23 / 72 / 83 / 95 ms 10 ms (4-channel mode); 95/83/72/23 ms (8-channel mode) 400 / 60 / 50 Hz, combinations of 400, 60, 50 Hz
shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel     Resolution with overrange (bit including sign), max.      Integration time, parameterizable     Basic conversion time (ms)     Interference voltage suppression for interference frequency f1 in Hz  Encoder  Connection of signal encoders     for voltage measurement	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign Yes; 23 / 72 / 83 / 95 ms 10 ms (4-channel mode); 95/83/72/23 ms (8-channel mode) 400 / 60 / 50 Hz, combinations of 400, 60, 50 Hz
shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel     Resolution with overrange (bit including sign), max.      Integration time, parameterizable     Basic conversion time (ms)     Interference voltage suppression for interference frequency f1 in Hz  Encoder  Connection of signal encoders     for voltage measurement	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign Yes; 23 / 72 / 83 / 95 ms 10 ms (4-channel mode); 95/83/72/23 ms (8-channel mode) 400 / 60 / 50 Hz, combinations of 400, 60, 50 Hz  Yes Yes; with external transmitter, current supply; possible with separate
shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel     Resolution with overrange (bit including sign), max.      Integration time, parameterizable     Basic conversion time (ms)     Interference voltage suppression for interference frequency f1 in Hz  Encoder  Connection of signal encoders     for voltage measurement     for current measurement as 2-wire transducer	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/
shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel     Resolution with overrange (bit including sign), max.      Integration time, parameterizable     Basic conversion time (ms)     Interference voltage suppression for interference frequency f1 in Hz  Encoder  Connection of signal encoders     for voltage measurement     for current measurement as 2-wire transducer     for current measurement as 4-wire transducer  Errors/accuracies	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/
shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel     Resolution with overrange (bit including sign), max.      Integration time, parameterizable     Basic conversion time (ms)     Interference voltage suppression for interference frequency f1 in Hz  Encoder  Connection of signal encoders     for voltage measurement     for current measurement as 2-wire transducer      for current measurement as 4-wire transducer  Errors/accuracies  Operational error limit in overall temperature range	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign Yes; 23 / 72 / 83 / 95 ms  10 ms (4-channel mode); 95/83/72/23 ms (8-channel mode)  400 / 60 / 50 Hz, combinations of 400, 60, 50 Hz  Yes Yes; with external transmitter, current supply; possible with separate supply for transmitter Yes
shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel     Resolution with overrange (bit including sign), max.      Integration time, parameterizable     Basic conversion time (ms)     Interference voltage suppression for interference frequency f1 in Hz  Encoder  Connection of signal encoders     for voltage measurement     for current measurement as 2-wire transducer      for current measurement as 4-wire transducer  Errors/accuracies  Operational error limit in overall temperature range     Voltage, relative to input range, (+/-)	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign Yes; 23 / 72 / 83 / 95 ms  10 ms (4-channel mode); 95/83/72/23 ms (8-channel mode)  400 / 60 / 50 Hz, combinations of 400, 60, 50 Hz  Yes Yes; with external transmitter, current supply; possible with separate supply for transmitter Yes  0.1 %
shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel     Resolution with overrange (bit including sign), max.      Integration time, parameterizable     Basic conversion time (ms)     Interference voltage suppression for interference frequency f1 in Hz  Encoder  Connection of signal encoders     for voltage measurement     for current measurement as 2-wire transducer      for current measurement as 4-wire transducer  Errors/accuracies  Operational error limit in overall temperature range     Voltage, relative to input range, (+/-)     Current, relative to input range, (+/-)	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign Yes; 23 / 72 / 83 / 95 ms  10 ms (4-channel mode); 95/83/72/23 ms (8-channel mode)  400 / 60 / 50 Hz, combinations of 400, 60, 50 Hz  Yes Yes; with external transmitter, current supply; possible with separate supply for transmitter Yes
shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel     Resolution with overrange (bit including sign), max.      Integration time, parameterizable     Basic conversion time (ms)     Interference voltage suppression for interference frequency f1 in Hz  Encoder  Connection of signal encoders     for voltage measurement     for current measurement as 2-wire transducer      for current measurement as 4-wire transducer  Errors/accuracies  Operational error limit in overall temperature range     Voltage, relative to input range, (+/-)     Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/
<ul> <li>shielded, max.</li> <li>Analog value generation for the inputs</li> <li>Integration and conversion time/resolution per channel</li> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Basic conversion time (ms)</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Operational error limit in overall temperature range</li> <li>Voltage, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Voltage, relative to input range, (+/-)</li> </ul>	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign Yes; 23 / 72 / 83 / 95 ms  10 ms (4-channel mode); 95/83/72/23 ms (8-channel mode)  400 / 60 / 50 Hz, combinations of 400, 60, 50 Hz   Yes Yes; with external transmitter, current supply; possible with separate supply for transmitter Yes  0.1 % 0.1 % 0.05 %
Shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel     Resolution with overrange (bit including sign), max.      Integration time, parameterizable     Basic conversion time (ms)     Interference voltage suppression for interference frequency f1 in Hz  Encoder  Connection of signal encoders     for voltage measurement     for current measurement as 2-wire transducer      for current measurement as 4-wire transducer  Errors/accuracies  Operational error limit in overall temperature range     Voltage, relative to input range, (+/-)     Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)     Voltage, relative to input range, (+/-)     Current, relative to input range, (+/-)     Current, relative to input range, (+/-)	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/
<ul> <li>shielded, max.</li> <li>Analog value generation for the inputs</li> <li>Integration and conversion time/resolution per channel</li> <li>Resolution with overrange (bit including sign), max.</li> <li>Integration time, parameterizable</li> <li>Basic conversion time (ms)</li> <li>Interference voltage suppression for interference frequency f1 in Hz</li> <li>Encoder</li> <li>Connection of signal encoders</li> <li>for voltage measurement</li> <li>for current measurement as 2-wire transducer</li> <li>for current measurement as 4-wire transducer</li> <li>Errors/accuracies</li> <li>Operational error limit in overall temperature range</li> <li>Voltage, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> <li>Basic error limit (operational limit at 25 °C)</li> <li>Voltage, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> <li>Current, relative to input range, (+/-)</li> </ul>	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign Yes; 23 / 72 / 83 / 95 ms  10 ms (4-channel mode); 95/83/72/23 ms (8-channel mode)  400 / 60 / 50 Hz, combinations of 400, 60, 50 Hz   Yes  Yes; with external transmitter, current supply; possible with separate supply for transmitter  Yes  0.1 %  0.05 %  0.05 %
Shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel     Resolution with overrange (bit including sign), max.      Integration time, parameterizable     Basic conversion time (ms)     Interference voltage suppression for interference frequency f1 in Hz  Encoder  Connection of signal encoders     for voltage measurement     for current measurement as 2-wire transducer      for current measurement as 4-wire transducer  Errors/accuracies  Operational error limit in overall temperature range     Voltage, relative to input range, (+/-)     Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)  Voltage, relative to input range, (+/-)     Current, relative to input range, (+/-)  Current, relative to input range, (+/-)  Interrupts/diagnostics/status information  Diagnostics function	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/15 bit + sign/15 bit + sign Yes; 23 / 72 / 83 / 95 ms  10 ms (4-channel mode); 95/83/72/23 ms (8-channel mode)  400 / 60 / 50 Hz, combinations of 400, 60, 50 Hz   Yes Yes; with external transmitter, current supply; possible with separate supply for transmitter Yes  0.1 % 0.1 % 0.05 %
Shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel     Resolution with overrange (bit including sign), max.      Integration time, parameterizable     Basic conversion time (ms)     Interference voltage suppression for interference frequency f1 in Hz  Encoder  Connection of signal encoders     for voltage measurement     for current measurement as 2-wire transducer      for current measurement as 4-wire transducer  Errors/accuracies  Operational error limit in overall temperature range     Voltage, relative to input range, (+/-)     Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)      Voltage, relative to input range, (+/-)     Current, relative to input range, (+/-)     Current, relative to input range, (+/-)     Interrupts/diagnostics/status information  Diagnostics function  Alarms	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/
Shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel     Resolution with overrange (bit including sign), max.      Integration time, parameterizable     Basic conversion time (ms)     Interference voltage suppression for interference frequency f1 in Hz  Encoder  Connection of signal encoders     for voltage measurement     for current measurement as 2-wire transducer      for current measurement as 4-wire transducer  Errors/accuracies  Operational error limit in overall temperature range     Voltage, relative to input range, (+/-)     Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)     Voltage, relative to input range, (+/-)     Current, relative to input range, (+/-)     Current, relative to input range, (+/-)     Interrupts/diagnostics/status information  Diagnostics function  Alarms     Diagnostic alarm	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/
Shielded, max.  Analog value generation for the inputs  Integration and conversion time/resolution per channel     Resolution with overrange (bit including sign), max.      Integration time, parameterizable     Basic conversion time (ms)     Interference voltage suppression for interference frequency f1 in Hz  Encoder  Connection of signal encoders     for voltage measurement     for current measurement as 2-wire transducer      for current measurement as 4-wire transducer  Errors/accuracies  Operational error limit in overall temperature range     Voltage, relative to input range, (+/-)     Current, relative to input range, (+/-)  Basic error limit (operational limit at 25 °C)      Voltage, relative to input range, (+/-)     Current, relative to input range, (+/-)     Current, relative to input range, (+/-)     Interrupts/diagnostics/status information  Diagnostics function  Alarms	16 bit; Unipolar: 15/15/15/15 bit; bipolar: 15 bit + sign/15 bit + sign/

Hardware interrupt	Yes; Parameterizable, channels 0 to 7 (on exceeding limit value), at end of cycle
Diagnoses	
<ul> <li>Diagnostic information readable</li> </ul>	Yes
Diagnostics indication LED	
<ul> <li>Group error SF (red)</li> </ul>	Yes
Potential separation	
Potential separation analog inputs	
<ul> <li>between the channels</li> </ul>	Yes
<ul> <li>between the channels, in groups of</li> </ul>	2
<ul> <li>between the channels and backplane bus</li> </ul>	Yes
<ul> <li>between the channels and the power supply of the electronics</li> </ul>	Yes
Isolation	
Isolation tested with	500 V AC
connection method / header	
required front connector	40-pin
Dimensions	
Width	40 mm
Height	125 mm
Depth	117 mm
Weights	
Weight, approx.	272 g
last modified:	1/17/2021 🗗