

## Tableau de sélection: Interrupteurs magnétiques

### Distances de commutation

Aimants de commande	BN 80-10Z	BN 80-01Z	BN 80-rz	BN 85-R	BN 310-10Z BN 310-01Z	BN 310-RZ	BN 32-10 BN 32-01 BN 32-11	BN 32-R BN 32-11R	BN 325-R	BN 65-10Z BN 65-10Z/1 BN 65-01Z	BN 65-RZ	BN 65-10Z/V BN 65-01Z/V	BN 65-RZ/V	BN 20-10Z BN 20-20Z BN 20-01Z BN 20-02Z BN 20-11Z	BN 20-RZ BN 20-2RZ BN 20-11RZ
BP 6 S			4-18	2-12											
BP 7 S			6-22												
BP 8	3-8	0-5													
BP 8 S				2-10											
BP 10	6-12	2-9	2-9		5		5			5					
<b>BP 10 N</b>						15		10	10		15				5
<b>BP 10 S</b>			10-30	5-20		15		10	10		15	5			5
<b>2 x BP 10</b>	12-20	2-13	2-13		17		12			17			3	12	
<b>2 x BP 10 N</b>						20		15	15		20				10
<b>2 x BP 10 S</b>			12-36	6-27		20		15	15		20	10			10
<b>BP 15</b>	8-14	2-10			6		6			6					
<b>BP 15 N</b>						17		12	12		17				7
<b>BP 15 S</b>			12-30	5-22		17		12	12		17	6			7
<b>2 x BP 15</b>	12-22	2-15			17		12			17					
<b>2 x BP 15S</b>			13-38	7-28											
<b>2 x BP 15/2</b>					17		12			17				12	
<b>2 x BP 15/2 N</b>						22		17	17		22				15
<b>2 x BP 15/2 S</b>						22		17	17		22				15
<b>BP 34</b>					5-20		15			15-20			15		
<b>BP 34 N</b>						15-30		10-25	10-25		15-30				10-25
<b>BP 34 S</b>			20-50	10-40		15-30		10-25	10-25		15-30	20			10-25
<b>2 x BP 34</b>	12-26	5-18													
<b>2 x BP 34 S</b>			22-60												
<b>BP 20</b>	12-24	0-14			20		15			20			10	15	
<b>BP 20 N</b>						3-25		5-20	5-20		25				15
<b>BP 20 S</b>			10-38	3-28		3-25		5-20	5-20		25	15			15
<b>BP 31</b>	12-24	0-14			20		15			20			10	15	
<b>BP 31 N</b>						3-25		5-20	5-20		25				15
<b>BP 31 S</b>			12-40	4-30		3-25		5-20	5-20		25	15			15
<b>BP 11</b>	22-28	2-16			8-20		5-15			20			15	15	
<b>BP 11 N</b>						15		10	10		15				5
<b>BP 11 S</b>			10-30	4-23		15		10	10		15	5			5
<b>2 x BP 11 N</b>						3-25		20	20		25				15
<b>2 x BP 11 S</b>						3-25		20	20		25	15			15
<b>BP 12</b>	24-32	4-20			10-30		10-25			10-30			20	25	
<b>BP 12 N</b>						20		15	15		20				10
<b>2 x BP 12 N</b>						10-30		10-25	10-25		10-30				5-20
<b>2 x BP 12 S</b>						10-30		10-25	10-25		10-30	25			5-20
<b>BP 21</b>					25-50		20-40			25-50			45	20-45	
<b>BP 21 N</b>						15-45		15-40	15-40		15-45				10-35
<b>BP 21 S</b>						15-45		15-40	15-40		15-45	30			10-35
<b>2 x BP 21 N</b>						20-60		20-55	20-55		20-60				15-50
<b>2 x BP 21 S</b>						20-60		20-55	20-55		20-60	20-55			15-50
<b>BP 22 S</b>												25			
<b>BP 22 N+BP 22 S</b>													35		
<b>2 x BP 22 S</b>												15-55			
<b>BE 20</b>					20		15						10	15	
<b>BE 20 N</b>						20		15	15		20				10
<b>BE 20 S</b>						20		15	15		20	6			10