F204 A-80/0,03-L



Products + Low Voltage Products and Systems + Modular DIN Rail Products + Residual Current Devices RCDs + Residual Current Devices RCDs

General Information

 Extended Product Type:
 F204 A-80/0,03-L

 Product ID:
 2CSF204123R1800

 EAN:
 8012542918608

Catalog Description: F204 A-80/0,03-L Residual Current Circuit Breaker

Long Description: The RCCBs F200 series assures protection to people and installations aga

inst fault current to earth. A large offer for standard instantaneous and sele ctive AC and A types is completed with some configurations for special app

lications.

Ordering

Minimum Order Quantity: 1 piece

Customs Tariff Number: 85363030

Popular Downloads

Data Sheet, Technical Information: 2CSC400002D0209

Instructions and Manuals: 2CSF423001D6406

Dimensions

Product Net Width: 0.070 m

Product Net Height: 0.085 m

Product Net Depth: 0.069 m

Product Net Weight: 0.380 kg

Technical

Standards: IEC/EN 61008

Operating Characteristic: Instantaneous

Type of Residual Current: A type

Rated Residual Current: 30 mA

Rated Current (I_n) : 80 A

Number of Poles: 4

Position of Neutral Terminals: Left

Power Loss: at Rated Operating Conditions per Pole 5.3 W

Environmental

Ambient Air Temperature: Operation -25 ... +55 °C

Storage -40 ... +70 °C

RoHS Status: Following EU Directive 2011/65/EU

Certificates and Declarations (Document Number)

Declaration of Conformity - CE: 9AKK106713A5602

Environmental Information: S-P-00081

Instructions and Manuals: 2CSF423001D6406

Container Information

Package Level 1 Units: 1 piece

Package Level 1 Width: 0.082 m

Package Level 1 Height: 0.078 m

Package Level 1 Length: 0.096 m

Package Level 1 Gross Weight: 0.423 kg

Package Level 1 EAN: 8012542918608

Classifications

Object Classification Code: Q

E-nummer: 2160001

ETIM 4: EC000003 - Residual current circuit breaker (RCCB)

ETIM 5: EC000003 - Residual current circuit breaker (RCCB)

ETIM 6: EC000003 - Residual current circuit breaker (RCCB)

ETIM 7: EC000003 - Residual current circuit breaker (RCCB)

