Product data sheet Characteristics

GV2AF3

TeSys GV2, interconnection block, to connect GV2 and LC1D09 to D38 contactor





Main	
Range	Linergy
Product name	FT
Device short name	GV2AF
Product or Component Type	Combination block
Accessory / separate part category	Connection accessory
Range compatibility	TeSys GV2 TeSys Deca

Complementary

Product Compatibility	LC1D09D38	
Poles description	3P	
[le] rated operational current	32 A	
Quantity per Set	Set of 10	
Net Weight	0.04 lb(US) (0.016 kg)	

Ordering and shipping details

Category	22367-MANUAL STR PROTECTOR - GV2
Discount Schedule	l11
GTIN	3389110569063
Returnability	Yes
Country of origin	FR

Packing Units

I acking Office	
Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	3.74 in (9.500 cm)
Package 1 Width	3.94 in (10.000 cm)
Package 1 Length	5.91 in (15.000 cm)
Package 1 Weight	0.78 oz (22.000 g)
Unit Type of Package 2	BB1
Number of Units in Package 2	10
Package 2 Height	3.74 in (9.500 cm)
Package 2 Width	3.94 in (10.000 cm)
Package 2 Length	5.91 in (15.000 cm)
Package 2 Weight	9.45 oz (268.000 g)
Unit Type of Package 3	S03
Number of Units in Package 3	140
Package 3 Height	11.81 in (30.000 cm)
Package 3 Width	11.81 in (30.000 cm)
Package 3 Length	15.75 in (40.000 cm)
Package 3 Weight	9.25 lb(US) (4.196 kg)

Offer Sustainability

Sustainable offer status	Green Premium product	
REACh Regulation	[™] REACh Declaration	
REACh free of SVHC	Yes	
EU RoHS Directive	Compliant EEU RoHS Declaration	
Toxic heavy metal free	Yes	
Mercury free	Yes	
China RoHS Regulation	China RoHS Declaration	
RoHS exemption information	€Yes	
Environmental Disclosure	Product Environmental Profile	
Circularity Profile	End Of Life Information	
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.	


Contractual warranty


Warranty	10 months
Warranty	18 months
	· · · · · · · · · · · · · · · · · · ·

GV2AF3

GV2AF01


Combination GV2ME + TeSys k contactor






GV2AF3

Combination GV2ME + TeSys d contactor



GV2ME +	LC1D09D18	LC1D25 and D32
b	176.4	186.8
c1	94.1	100.4
С	99.6	105.9

Combination GV2P + TeSys d contactor



GV2P +	LC1D09D18	LC1D25 and D32
b	176.4	186.8
c1	100.1	106.4
С	105.6	111.9
d1	95	95
d	100.5	100.5